



CAST Mini I/O Unit

Part No. **CA734**



T 01942 322744 E sales@c-tec.co.uk
F 01942 829867 W www.c-tec.com



C-TEC, Challenge Way, Martland Park, Wigan, WN5 0LD United Kingdom



 L2- L1- L2+ L1+
CA734 Mini IO Unit Fault
 Loop Address:
 176j/01 Poll/Active
 EN54-17:2005 EN54-18:2005
 0832-CPR-F2049
 WO: xxxxxxx Warr:xx/xx/xx
 Relay Max See DFU7340010
 1A @ 30 V d.c. or Made in UK
 0.3A @ 125 V a.c.
 CE 17

SW	LED	Relay
+	+	O Z O Z



Overview



T 01942 322744 E sales@c-tec.co.uk
 F 01942 829867 W www.c-tec.com



C-TEC, Challenge Way, Martland Park, Wigan, WN5 0LD United Kingdom



- LPCB certified to EN54-17 & 18 and Kiwa Telefication certified to EN54-13.
- Includes a switch monitor, signal relay and onboard loop isolator.
- 7mA typical alarm current (1mA typical quiescent current) @ 22-40V DC.
- Four plastic tabs for surface or panel mounting.
- Includes a 1A 30V DC volt-free changeover relay. Can also switch 0.3A @125V AC.
- Offers Switch +Ve, -Ve, LED +V, -Ve and changeover relay connections
- Future header pin offers expansion opportunities for peripheral I/O devices.



More Information

'CAST' is the world's most-advanced 'distributed intelligence' fire alarm system protocol. Conceived, designed and realised by C-TEC as part of a five-year, multi-million pound project, it involved the creation of a powerful proprietary communication protocol (C-TEC Addressable System Technology, CAST) and multiple control panels & field devices. Now available to purchase, its key features include: • 255 devices per loop. • Autonomous decision-making for faster response times. • Multiple type codes. • 40V loop drive voltage. • Two 'soft' addressing options - automatic via the panel or manual via a powerful handheld programmer. • Powerful multi-level addressing facilitates easy device addition and swapped device identification. • Multiple functionality at a single address (integrated devices) - coming soon. • Volumes, tones & detector modes can be changed at compatible panels. • High-speed data transmission and robust data transfer. • Intrinsically EN54-13 compliant. • Provides geographical location of short and open circuit faults (a short circuit isolator is included as standard in every CAST field device). • Replace device function. • Future seamless integration with other CAST life safety systems reducing energy, servicing, installation and repair costs. • Designed and manufactured in the UK.

Technical Specifications

Approvals/certifications	LPCB certified to EN54-17 & 18 and Kiwa Telefication certified to EN54-13.
Compatibility	Compatible with C-TEC's XFP/ZFP CAST Addressable Fire Panels.
Supply/operating voltage	22 to 40V DC.
Quiescent current	1mA typical.
Activation current	7mA @ 22 to 40V DC..
Auxiliary relays	One volt-free single pole changeover relay rated at 1A @ 30V DC (or 0.3A @ 125V AC). Non-monitored. Clean contact.
Auxiliary inputs	One monitored input that can be set to operate as: (1) a single zone monitor to support up to 20 ActiV detectors and 10 MCPs or (2) a monitored normally-open switch, triggered by a 470R.
Indicators	Single Red (Relay Active & Polling); Single Yellow (Monitored Input Fault).
Product dimensions (mm)	65 W x 65H x 20 D mm (excluding terminal block & ribbon cable). Ribbon cable is 150 mm length.
Construction & finish	Clear ABS polycarbonate enclosure.
IP Rating	IP40.
Weight	47g.
Operating conditions/temperature	-10°C to +55°C.



T 01942 322744 E sales@c-tec.co.uk
F 01942 829867 W www.c-tec.com



C-TEC, Challenge Way, Martland Park, Wigan, WN5 0LD United Kingdom