

## CW1-PF-T MAINS POWERED CARBON MONOXIDE ALARM + PUSH FIT BASE

<b>Sensor type</b>	Electrochemical
<b>Battery type</b>	Mains powered with 9V battery back-up

The CW1-PF is a mains powered carbon monoxide alarm with high performance electrochemical sensor, 9V zinc carbon battery back-up and an improved PUSH-FIT base for quicker and easier installations; designed to ensure quick and easy installation of base unit to the mains feed supply at installation stage (1st fix) and for quicker and easier connection of alarm to base unit (2nd fix). Providing early warning of the presence of CO in the home through alarm and LED display.



- 230V mains powered carbon monoxide alarm
- 9V battery back-up
- Improved PUSH-FIT base for quicker installations
- Electrochemical sensing technology
- Large central test button makes weekly testing easy
- LED operating indicators - Power, Fault, Alarm
- Low battery warning indicator
- Multi-alarm interconnect up to 12 smoke (SW1-PF), heat (HW1-PF) & CO (CW1-PF) units – when one sounds they all sound
- Safety clip feature, to prevent installation of smoke alarm without battery installed
- 5 year warranty
- EN 50291-1: 2018

## Technical Specification

<b>Dimensions</b>	126mm (diameter) x 49mm (depth)
<b>Model number</b>	CW1-PF-T
<b>Description</b>	230V CO with zinc carbon battery back-up
<b>Technology</b>	Electrochemical
<b>Alarm sound level</b>	85db at 3 metres
<b>Battery type</b>	9V PP3 zinc carbon
<b>Operation AC/DC</b>	AC
<b>Installation positions</b>	Ceiling
<b>Operating temperature</b>	0°C (32°F) to 40°C (104°F).
<b>Operating humidity</b>	TBC
<b>Storage temperature</b>	TBC
<b>Storage humidity</b>	TBC
<b>Warranty</b>	5 years
<b>Approvals</b>	EN 50291-1: 2018